


COUNTY

COUNTY is a microcomputer based instrument which counts axial, radial and SMD (with 8301.018 option) components.

TECHNICAL FEATURES

Counting in both directions (left or right)
 Divider from 1 to 19
 TOTALIZER mode counting
 PRESET mode counting (with an audible alarm when the desired component number is reached)
 Calibration test and self diagnostic procedure
 Last counting value and condition memory
 Rechargeable model available (8301.072 and .074)
 Relay output

Maximum counting value:	899999 counts
Minimum lead diameter:	0.4 mm
Axial component bandolier width:	55 - 110 mm
Radial component bandolier width:	max 18 mm
Maximum component diameter:	14 mm
Display:	4 digits 13 mm height
Dimensions:	240 x 130 x 110 mm
Weight:	1.8kg



AXIAL COUNTING

The plastic mobile guide is adjusted for axial counting (see above). For bandolier counting the 8301.023 support is available, with an easily inserted 8301.025 handle (see figure on right).

RADIAL COUNTING

The plastic mobile guide is adjusted for radial counting (see figure on the right). Before counting it is necessary to select the lead component number by setting the divider.

SMD COUNTY ADAPTOR

The County adaptor for counting taped SMD components is an optional accessory for the County Component Counter.

The maximum tape height is 56mm and the number of hole per component is min 0.5 - max 19.

Mounting the adaptor does not require any tools and it is locked in place by snap action.


Component counting is achieved by counting the punched holes on the SMD tapes.

8301.028 rotating SMD supports and 8301.030 SMD bandolier handle are optional items.



SUPPORT FOR ROLLED BANDOLIER

LABEL PRINTER



RADIAL COUNTING



- | | |
|----------|---|
| 8301.051 | COUNTY 220 V 50-60 Hz |
| 8301.072 | COUNTY 220 V 50 - 60 Hz
with accumulator, auxiliary relay, printer output, watch |
| 8301.053 | COUNTY 110 V 50 - 60 Hz |
| 8301.074 | COUNTY 110 V 50 - 60 Hz
with accumulator, auxiliary relay, printer output, watch |
| 8301.023 | Complete support for rolled bandolier(1 pcs) |
| 8301.025 | Bandolier handle |
| 8301.018 | SMD County Adaptor |
| 8301.028 | SMD support for rolled bandolier |
| 8301.030 | SMD bandolier handle |
| 8301.350 | ISO9000 Traceable® Certificate |